

## Solution to Homework 41

**Homework 41.** On the example of the negation function  $f(x) = \neg x$ , trace, step by step, how Deutsch-Josza algorithm will conclude that  $f(0) \neq f(1)$  while applying  $f$  only once.

**Solution.** The Deutsch-Josza algorithm consists of the following steps:

- we start with the state  $|0, 1\rangle = |0\rangle \otimes |1\rangle$ ;
- we apply the Hadamard transformation  $H$  to both bits, i.e., the transformation for which

$$H(|0\rangle) = \frac{1}{\sqrt{2}}|0\rangle + \frac{1}{\sqrt{2}}|1\rangle; \quad H(|1\rangle) = \frac{1}{\sqrt{2}}|0\rangle - \frac{1}{\sqrt{2}}|1\rangle;$$

- then, we apply the function  $f$ , i.e., apply the transformation

$$f(|x, y\rangle) = |x, y \oplus f(x)\rangle,$$

where  $a \oplus b$  means addition modulo 2 or, equivalently, exclusive “or”:

$$0 \oplus 0 = 0; \quad 0 \oplus 1 = 1 \oplus 0 = 1; \quad 1 \oplus 1 = 0;$$

- after that, we again apply the Hadamard transformation to both bits;
- finally, we measure the first bit of the resulting 2-bit state:
  - if the first bit is 0, we conclude that the function  $f$  is constant;
  - if the first bit is 1, we conclude that the function  $f$  is not constant.

According to the handout, after applying the Hadamard transformation  $H$  to both bits of the state  $|0, 1\rangle = |0\rangle \otimes |1\rangle$ , we get the state

$$H(|0\rangle) \otimes H(|1\rangle) = \frac{1}{2}|0, 0\rangle - \frac{1}{2}|0, 1\rangle + \frac{1}{2}|1, 0\rangle - \frac{1}{2}|1, 1\rangle. \quad (1)$$

When we apply the function  $f$ , we get the following:

$$f(|0, 0\rangle) = |0, 1\rangle, \quad f(|0, 1\rangle) = |0, 0\rangle, \quad f(|1, 0\rangle) = |1, 0\rangle, \quad f(|1, 1\rangle) = |1, 1\rangle.$$

Thus, the state (1) gets transformed into

$$f(H(|0\rangle) \otimes H(|1\rangle)) = \frac{1}{2}|0, 1\rangle - \frac{1}{2}|0, 0\rangle + \frac{1}{2}|1, 0\rangle - \frac{1}{2}|1, 1\rangle =$$

$$-\frac{1}{2}|0\rangle \otimes |0\rangle + \frac{1}{2}|0\rangle \otimes |1\rangle + \frac{1}{2}|1\rangle \otimes |0\rangle - \frac{1}{2}|1\rangle \otimes |1\rangle.$$

The first two terms have a common factor  $|0\rangle$ , the third and the fourth one have a common factor  $|1\rangle$ , so we have

$$f(H(|0\rangle) \otimes H(|1\rangle)) = -\frac{1}{\sqrt{2}}|0\rangle \otimes \left( \frac{1}{\sqrt{2}}|0\rangle - \frac{1}{\sqrt{2}}|1\rangle \right) + \frac{1}{\sqrt{2}}|1\rangle \otimes \left( \frac{1}{\sqrt{2}}|0\rangle - \frac{1}{\sqrt{2}}|1\rangle \right).$$

This expression can be equivalently reformulated as

$$f(H(|0\rangle) \otimes H(|1\rangle)) = -\left( \frac{1}{\sqrt{2}}|0\rangle - \frac{1}{\sqrt{2}}|1\rangle \right) \otimes \left( \frac{1}{\sqrt{2}}|0\rangle - \frac{1}{\sqrt{2}}|1\rangle \right).$$

For both bits, what we have is  $H|1\rangle$ :

$$f(H(|0\rangle) \otimes H(|1\rangle)) = -H(|1\rangle) \otimes H(|1\rangle).$$

It is known that when we apply the Hadamard transformation twice, we get back the original state. In particular,  $H(H(|1\rangle)) = |1\rangle$ . Thus, when we apply the Hadamard transformation to both bits once again, we get the state

$$-|1\rangle \otimes |1\rangle.$$

Measuring the value of the first bit, we get the value 1 with probability  $|-1|^2 = 1$ . Thus, we can indeed conclude that  $f(0) \neq f(1)$  – and we called the function  $f$  only once.