

## Solution to Problem 23

**Problem.** logarithms were invented to make multiplication and division faster: they reduce:

- multiplication to addition and
- division to subtraction

by using the formulas

$$\ln(x_1 \cdot x_2) = \ln(x_1) + \ln(x_2) \text{ and } \ln(x_1/x_2) = \ln(x_1) - \ln(x_2).$$

Specifically:

- instead of directly computing the product  $y = x_1 \cdot x_2$ , we first compute  $X_1 = \ln(x_1)$  and  $X_2 = \ln(x_2)$ , then compute  $Y = X_1 + X_2$ , and then  $y = \exp(Y)$ ;
- instead of directly computing the ratio  $y = x_1/x_2$ , we first compute  $X_1 = \ln(x_1)$  and  $X_2 = \ln(x_2)$ , then compute  $Y = X_1 - X_2$ , and then  $y = \exp(Y)$ .

Describe each of these two reductions in general terms: what is  $C(x, y)$ , what is  $C'(x', y')$ , what is  $U_1$ ,  $U_2$ , and  $U_3$ .

**Solution for the product.** Here  $x = (x_1, x_2)$ ,  $C(x, y)$  is the desired property  $y = x_1 \cdot x_2$ . For the problem to which we reduce, we have  $x' = (X_1, X_2)$ ,  $y' = Y$ , and the property  $C'(x', y')$  is  $Y = X_1 + X_2$ .

Here,  $U_1(x_1, x_2) = (\ln(x_1), \ln(x_2))$ ,  $U_2(Y) = \exp(Y)$ , and  $U_3(y) = \ln(y)$ .

**Solution for the ratio.** Here  $x = (x_1, x_2)$ ,  $C(x, y)$  is the desired property  $y = x_1/x_2$ . For the problem to which we reduce, we have  $x' = (X_1, X_2)$ ,  $y' = Y$ , and the property  $C'(x', y')$  is  $Y = X_1 - X_2$ .

Here,  $U_1(x_1, x_2) = (\ln(x_1), \ln(x_2))$ ,  $U_2(Y) = \exp(Y)$ , and  $U_3(y) = \ln(y)$ .